



ORPHEUS THREE S V2

USER MANUAL



INTRODUCTION

CONTENTS

- Introduction2
- Front panel description3
- Rear panel description4
- Connections5
- Operations6

UNPACKING

First check and identify the contents of your Orpheus Three package, as listed below :

- Orpheus Three power amplifier
- Orpheus Three CD user's manual

If any item should be damaged or missing, please inform your supplier without delay.

Keep the packing materials, you may need it to transport the unit in the future.

READ THIS BEFORE OPERATING YOUR UNIT

- Please read this manual carefully, to assure proper operation and the best possible performance.
 - Switch off the unit before connecting or disconnecting any input or output wire.
 - Do not touch the inner pins of rear-panel connectors, electrostatic discharge may cause permanent damage to the unit.
 - Choose the installation location for the unit carefully. Avoid placing it in direct sunlight or close to a source of heat. Avoid also locations subject to vibration and excessive dust, heat, cold or moisture.
 - To reduce the risk of fire or electric shock, do not expose the unit to rain or moisture.
 - Do not use force when operating switches, knobs and other controls.
 - Do not open the chassis or attempt to make repairs by yourself, as this may result in damage to the unit or electrical shock. If a foreign object should get into the unit, contact your local dealer.
 - When planning not to use the unit for a long period of time, it is advisable to disconnect the power plug from the wall outlet.
 - The power switch does not disconnect the complete unit from the main line.
 - To prevent lightning damage, disconnect the power plug when there is an electrical storm.
- When moving the unit, be sure to first disconnect the power plug and all wires connected from the unit to other equipment.
 - When disconnecting the power plug from the wall outlet, always pull directly on the plug, never pull the cord itself.
 - Do not attempt to clean this unit with water or chemical solvents, as this may damage the unit or the finish. Use a clean, dry cloth.
 - Keep this manual in a safe place for future reference.

FRONT PANEL



1. LEFT POWER INDICATOR

Lights red when the unit is switched on and operating.

Blinks red during the self-test procedure (approximately 2 seconds) after switching on the unit.

Indicator light is off when the unit is switched off.


2. RIGHT POWER INDICATOR

Lights red when the unit is switched on and operating.

Blinks red during the self-test procedure (approximately 2 seconds) after switching on the unit.

Indicator light is off when the unit is switched off.

REAR PANEL



1. INPUT SELECTOR SWITCH

Press the switch either to the left to select the unbalanced input or to the right to select the balanced input.

2. INPUT

Balanced and unbalanced input connectors.

3. OUTPUT


Dual output connectors in parallel.

4. POWER SUPPLY, INPUT VOLTAGE SELECTOR & FUSE RECEPTACLE

The input voltage selector connector configures the unit to the line voltage of the country where it is used.

The main fuse is located in the fuse receptacle. If it has to be changed, replace it by a T10A slow-blow fuse.

CONNECTIONS



OPERATIONS/ SPECIFICATIONS

QUICK GUIDE

CONNECTION

Connect the input cable from the preamplifier first, followed by the output cable to the loudspeakers, and finally the power cord.

INPUT FORMAT

Select either the unbalanced input on RCA connector or the balanced input on XLR connector by flipping the switch left or right respectively.

POWER ON

Flip the main power switch at the back of the unit from 0 to I.

The main power indicator on the front panel will light red and then green when ready for operation.

TECHNICAL DATA

Max Power : 2 x 150 W RMS

Sensitivity : 1 V RMS for an 8Ω load

Voltage gain

+ 39.70 or + 32.00 dB @ 16Ω load

+ 34.40 or + 30.70 dB @ 8Ω load

+ 27.10 or + 28.70 dB @ 4Ω load

+ 17.20 or + 24.70 dB @ 2Ω load

Measure reference : 1W in an 8Ω load = 0dBr

THD+N @ 0dBr : 0.007%

THD+N @ -30dBr : 0.070%

THD+N @ -60dBr : 1.700%

Dynamic range : 95dB

Signal/noise ratio : 95dB

Residual noise: 46μV RMS (A-weighted)

Measure reference : 30W in a 4Ω load = 0 dBr

THD+N @ 0dB : 0.006%

THD+N @ -30dBr : 0.016%

THD+N @ -60dBr : 0.350%

Dynamic range : 109dB

Signal/noise ratio : 109dB

Residual noise: 38μV RMS (A-weighted)

Power supply:

Selectable AC volatge: 100 / 115 / 230 VAC

Idle Power from main: 57 W RMS

Max Power from main: 700 W RMS

Output stage:

Maximum voltage swing: 120 V peak to peak

Frequency response: +/- 0.1 dB @ 0 - 20KHz

Slew rate: > 100 V/uS

Operating temperature: -30°C to +40°C

Safety: Fuses 10 A slow blow (T10A)

Size and weight:

Dimensions: 440 W x 370 D x 115 H (mm)

Weight: 24 Kg

Warranty: 1 year parts and labour

OPERATIONS

COMMENTS

Constructive feedback is always welcome.

Please feel free to forward us your comments at the address listed below or to your local dealer or distributor.

TECHNOLOGY & DESIGN

The unit has been entirely manufactured and assembled in Switzerland; conceived by ANAGRAM Technologies SA and designed by Chiarini Design.

IMPORTANT NOTICE

Orpheus Laboratories Sàrl reserve the right to make changes to their products or discontinue any product or service without notice. Adequate operating safeguards must be used to minimize hazards. Reproduction of user manual information is permissible only if it is without alteration and is accompanied by all relevant conditions, limitations and notices. Source must be clearly identified when reproducing user manual information.

ADDRESS

ORPHEUS MEDIA Sàrl
Av. des Sciences 3
1400 Yverdon-les-Bains
Switzerland

+41 24 423 90 88 phone
+41 21 423 90 89 fax

info@orpheuslab.com
www.orpheuslab.com

DEALER/DISTRIBUTOR

© Orpheus Media Sàrl - 2006
March 2006 - rev. 3